



# IFB Client for iOS

Review, 20 Feb 2023 for Ver 1.3 (or above)

## STREAMBOX IFB SYSTEM OVERVIEW

The interruptible fold back system allows an audio feed to be sent to a reporter in the field. The audio feed can then be monitored by the reporter using an in-ear monitor. This allows the reporter to receive cues and other information from the news bureau or headquarters. Streambox IFB System is part of a complete satellite news gathering solution.

Streambox has updated their IFB client application for iOS. Here are steps for review:

### Install the IFB Client

The UI contains the following items (image on right):

Presets menu: Select from a list of presets


Settings menu: Access settings pages

Stop button: Stop IFB input

Mute switch button: Mute audio without breaking connection


Lock switch button: Lock app UI until Unlock

Audio meters: Visual for audio incoming/levels



### Add Channel

1. Select 'Settings' menu
2. Select 'Preset Setup'
3. Select the desired Preset (Preset 1...Preset 20)
4. Set the 'Active' switch ON (i.e., this allows for a Preset to be defined and not displayed)
5. Name: Provide a meaningful name (e.g., My IFB Ch-1)
6. Server: Provide a valid IPv4 server address (for test, use 96.79.192.49)
7. Channel: Select a Channel (for review, we will provide audio on Channels #1 - #6)
8. Password: Provide a password (for review, you can enter the word 'empty')



9. Click the 'SAVE' button, then 'Done'


### Select a Preset

1. Select 'Presets' menu (from home screen)
2. Select desired 'Preset' (IFB audio should start in 1 to 10 seconds)

### Change Audio Codec

The audio codecs provide range for low bandwidth (low quality) to high bandwidth (high quality): GSM8, Speex8, Speex16, Speex32.

1. Select 'Settings' Menu
2. Select 'Advanced Settings'
3. Select the desired 'Codec'
4. Click 'Save' button



### Remote Sync Presets (populate Presets with a remotely located XML file)

1. Select 'Settings' Menu
2. Select 'Advanced Settings'
3. Enter a URL location of the XML file. For example, you could use an xml (sync) file located on Dropbox and then copy and paste the Dropbox link (Note: the last digit, usually 0, is set to 1 for download E.g., <https://www.dropbox.com/s/<dropbox id>?/<ifb-sync.xml>?dl=1>)
4. Click 'Sync Now'
5. If you set Sync ON, the IFB app will attempt to update the list each time the app is loaded.

### Sync XML Format

- **active="1"** designates active/visible channels, "0" for disabled channel
- **name=" "** friendly name of channel
- **ip=" "** public IPv4 of IFB server
- **password=" "** password for IFB server
- **channel="1"** Channel number (1 to 20)
- **buffersizems="1050"** Buffer size (1050 default)
- **codec="0"** Audio codec (0=GSM8, 1=Speex8, 2=Speex16, 3=Speex32)

### Sync XML Example

```
<?xml version="1.0" encoding="UTF-8" standalone="yes" ?>
<root>
  <ifbChannels active="1">
    <ifbChannel name=" " ip=" " password=" " channel="1" buffersizems="1050" codec="0"/>
  </ifbChannels>
  ...
  <ifbChannels active="1">
    <ifbChannel name=" " ip=" " password=" " channel="20" buffersizems="1050" codec="3"/>
  </ifbChannels>
</root>
```

## About Page

From the 'Settings' menu select 'About...'

## Contact Information

+1 206.956.0544 Tel

+1 206.956.0570 Fax

Sales and Information

[sales@streambox.com](mailto:sales@streambox.com)

+1 206.956.0544, Option 1

Technical Support

[beta@streambox.com](mailto:beta@streambox.com)

[support@streambox.com](mailto:support@streambox.com)

+1 206.956.0544, Option 2

Corporate Headquarters

1801 130th Ave NE, #200

Bellevue, WA 98005

## Privacy Notice

<http://www.streambox.com/streambox-inc-privacy-policy/>